**Dieses Dokument ist eine Zweitveröffentlichung (Verlagsversion) /
This is a self-archiving document (published version):**

J. Czarske, C. Leithold, Hannes Radner, L. Büttner, Moritz Stürmer, U. Wallrabe

**Undisturbed interferometric sensing through a fluid interface by
electrically-tunable lenses and micro mirrors**

Erstveröffentlichung in / First published in:

SPIE OPTO. San Francisco, 2015. Bellingham: SPIE, Vol. 9366 [*Zugriff am: 23.05.2019*].

DOI: <https://doi.org/10.1117/12.2077496>

Diese Version ist verfügbar / This version is available on:

<https://nbn-resolving.org/urn:nbn:de:bsz:14-qucosa2-349965>

„Dieser Beitrag ist mit Zustimmung des Rechteinhabers aufgrund einer (DFGgeförderten) Allianz- bzw. Nationallizenz frei zugänglich.“

This publication is openly accessible with the permission of the copyright owner. The permission is granted within a nationwide license, supported by the German Research Foundation (abbr. in German DFG).

www.nationallizenzen.de/

PROCEEDINGS OF SPIE

[SPIDigitalLibrary.org/conference-proceedings-of-spie](https://www.spiedigitallibrary.org/conference-proceedings-of-spie)

Undisturbed interferometric sensing through a fluid interface by electrically-tunable lenses and micro mirrors

J. Czarske, C. Leithold, Hannes Radner, L. Büttner, Moritz Stürmer, et al.

J. Czarske, C. Leithold, Hannes Radner, L. Büttner, Moritz Stürmer, U. Wallrabe, "Undisturbed interferometric sensing through a fluid interface by electrically-tunable lenses and micro mirrors," Proc. SPIE 9366, Smart Photonic and Optoelectronic Integrated Circuits XVII, 93660D (27 February 2015); doi: 10.1117/12.2077496

SPIE.

Event: SPIE OPTO, 2015, San Francisco, California, United States

Undisturbed interferometric sensing through a fluid interface by electrically-tunable lenses and micro mirrors

J. Czarske¹ *, C. Leithold¹, H. Radner¹, L. Büttner¹, M. Stürmer², U. Wallrabe²

¹ TUD Laboratory for Measurement and Testing Techniques, TUD Faculty of Electrical and Computer Engineering, TUD School of Engineering, TU Dresden, Helmholtzstraße 18, 01069 Dresden, Germany, *juergen.czarske@tu-dresden.de

² Laboratory for Microactuators, Institute for Microsystems Technology (IMTEK), Albert-Ludwigs-Universität Freiburg, Georges-Köhler-Allee 102, 79110 Freiburg

ABSTRACT

We have harnessed the power of various programmable photonics devices for an interferometric measurement technique. Distortion-free laser-based velocity measurements through a dynamic gas-liquid interface are enabled by a closed-loop optoelectronic system. We are employing electrically tunable lenses and micro mirrors to correct low-order wavefront distortions effectively. Our work represents a paradigm shift in interferometric velocity measurement techniques from using static to dynamic optical elements.

Keywords: adaptive optics; tunable membrane lens; Mach Zehnder interferometer

1. INTRODUCTION

Laser interferometers have become a well-established and indispensable tool for precision measurements in a huge variety of scientific and industrial applications, especially in fluid mechanics. Common measurands are displacement and velocity, which are proportional to the interference signal phase and frequency, respectively. It is well known that temperature, pressure and concentration variations of the ambient air change the refractive index [1]. Typical examples in the area of fluid mechanics are temperature gradients in combustions and pressure gradients at shock waves in compressible fluids. Beside such refractive index gradients also fluctuating interfaces between two media of different optical density have to be considered. Typical examples in fluid mechanics are water channel flows with an open surface, multi-phase flows, blood flows, levitated oscillating droplets and flows alongside a phase boundary. These variations cause severe distortions of the optical wavefronts, which can result in a failure or not tolerable uncertainties of the measurements. To overcome these challenging metrological problems, the employment of adaptive optics (AO) for a smart laser interferometer is proposed. AO is predominantly known from astronomy, where it has boosted the capabilities of modern earth-bound telescopes [2–5]. In general, an AO system comprises a wavefront sensor to measure the distortion of the wavefronts, an electric control circuit and an optical modulator to correct the distortions. Wavefront distortions caused by turbulent fluctuations of the earth's atmosphere are compensated resulting in a nearly diffraction-limited performance. A further prominent area of AO is ophthalmology. The correction of the eye aberrations enables to resolve single cells in the retina e.g., by using confocal microscopy [6] or optical coherence tomography (OCT) [7].

Also in technical metrology AO has been employed already. At optical roughness, measurements of technical surfaces the aberrations along the propagation direction of the laser beam have been corrected [8,9]. Also for flow measurements AO has been used [10–12]. First approaches have been demonstrated at laser Doppler velocimetry (LDV). AO was inserted to compensate for the random measurement deviation due to temperature gradients of heated air [10]. The LDV has been used to study gas flow stratifications. Recently, modern AO systems have been employed for an interferometric LDV [11,12]. The deployed AO devices were supplied by Flexible Optical B.V. (OKO tech, The Netherlands) and consist of a deformable membrane mirror with integrated tip-tilt stage, a Hartmann-Shack wavefront sensor and a controller based on a PC. This adaptive LDV provide flow velocity measurements through fluctuating gas-liquid interfaces inside a water basin or channel with an open surface [11]. The distortions of the propagating laser beams due

to the water surface waves have been corrected successfully, but to wave heights of only a few 10 microns [12]. At some tasks in fluid mechanics higher wave heights appear, resulting in larger amplitudes of optical distortions. In this paper we present a different approach for an adaptive, smart, interferometric LDV to overcome the former limitations. A novel electrically tunable lens and a commercially available galvanometer steering mirror are used to provide a large stroke for the wavefront correction.

For the first time, we investigate the hypothesis that electrically tunable lenses and steering mirrors enable the correction of large optical distortions in interferometry. The presented smart LDV interferometer will enable accurate flow velocity measurements through disturbing media interfaces especially at fluctuating gas-liquid interfaces. It faces large optical wavefront distortions caused by high surface waves of liquid flows, e.g., at film cooling processes, seawater salt removal, fractional distillation or processes to cool reactors.

2. VELOCITY MEASUREMENTS THROUGH A FLUCTUATING GAS-LIQUID INTERFACE

2.1 Preconsiderations

The flow velocity is gathered by an interferometric LDV technique, which allows high spatial and temporal resolutions together with a low velocity measurement uncertainty. The basic principle is to intersect two coherent laser beams under a small angle, forming a Mach-Zehnder interferometer. In the volume of intersection, a system of almost parallel interference fringes develops. If a particle carried with the flow to be investigated passes through the intersection volume of the laser beams, it scatters light that is modulated in amplitude with the Doppler frequency f . The velocity component v_x perpendicular to the interference fringe system orientation is resulting to

$$v_x = f \cdot d, \quad (1)$$

with the measured Doppler frequency f [13]. The a-priori calibrated interference fringe spacing d is calculated by

$$d = \frac{\lambda}{2 \sin \theta} \left(1 + \frac{z \cos^2 \theta (z \cos^2 \theta - z_w)}{z_R^2 \cos^2 \theta - z_w (z \cos^2 \theta - z_w)} \right), \quad (2)$$

with λ as the laser wavelength, θ as the intersection half angle of the interfering laser beams, z as the axis along the bisecting line of the two laser beams, z_w as the axial shift of the beam waist position relative to the center of the measurement volume and z_R as the Rayleigh length of the Gaussian laser beams, which is defined by $z_R = \pi w_0^2 / \lambda$, where w_0 is the radius of laser beam waists [13].

Considering the propagation of the laser beams through an open water surface to measure the flow velocity inside the water basin, the measurement properties of an LDV are changed by a moving air-water interface. In order to evaluate the contributions of different effects, the height function $h(x, t)$ of the air-water interface is developed into a Taylor series. This procedure is in analogy to the representation with Zernike polynomials. For simplification, only the one-dimensional expression is considered:

$$h(x, t) = \underbrace{h(x_0, t)}_{\text{Stroke}} + (x - x_0) \underbrace{\left. \frac{\partial h(x, t)}{\partial x} \right|_{x=x_0}}_{\text{Tilt}} + \frac{1}{2} (x - x_0)^2 \underbrace{\left. \frac{\partial^2 h(x, t)}{\partial x^2} \right|_{x=x_0}}_{\text{Curvature}} + \dots \quad (3)$$

The optical distortions caused by the fluctuating air-liquid interface can deteriorate the measurement properties as follows:

- 0th order: Height or stroke of the air-water interface. For a lift of the interface a parallel shift of the beam occurs whereas the beam direction remains constant. The consequence is a shift of the position of the measurement volume, i.e., a dislocation of the measurement position. Furthermore a signal frequency jitter is introduced, when the air-water interface is moving up or down.

- 1st order: Tilt of the air-water interface. Due to refraction, a tilt of the interface will change the propagation direction of the laser beam. Going to the two-dimensional consideration, it has to be distinguished between a tilt in the plane spanned by the two partial beams δx and a tilt in the direction normal to this plane δy .

(a) Tilt δx in x-direction (tip):

On one side a displacement of the measurement position results and on the other side there is a change in the intersection half angle θ of the interfering laser beams. Due to a change of the Rayleigh length z_R or the beam waist position z_w a variation of interference fringe spacing d results, see Equation (2). The standard deviation σ_d represents these variations. Using Equation (1) and the propagation law of statistical independent measurement, uncertainties of the fringe spacing σ_d and the signal frequency σ_f the relative velocity measurement uncertainty yields to [13]

$$\frac{\sigma_{v_x}}{v_x} = \sqrt{\left(\frac{\sigma_f}{f}\right)^2 + \left(\frac{\sigma_d}{d}\right)^2} \quad (4)$$

(b) Tilt δy in y-direction:

A beam deflection in the y-direction normal to the plane spanned by the two Gaussian beams will result in skew rays. The reduced overlap of the partial laser beams results in lower interference visibility and signal-to-noise ratio (SNR). Only measurement signals with a sufficient SNR are considered for further evaluation. The corresponding validation rate is given by the ratio between the evaluable and all signals detected. It represents a crucial figure-of-merit of the LDV system, since on the one hand the maximum frequency bandwidth of the velocity fluctuations and on the other the effective measurement time is determined. In the worst case of negligible laser beam overlapping no measurements can be performed at all, represented by a validation rate of zero.

- 2nd order: Parabolic curvature of the interface. Due to refraction, a curvature of the interface induces a lens effect on the beam propagation. It changes the radius of the beam waist w_0 and the position z_w of the beam waist. As a consequence, the fringe spacing d is changed according to Equation (2), which in general enhances the velocity measurement uncertainty, see Equation (4).
- 3rd order and higher orders: Distortions of the surface with high spatial frequency. The wavefront of the laser beams will be locally distorted, leading to inhomogeneities in the interference fringes. The fringe spacing can vary in all three directions. In consequence, the measurement uncertainty will increase, see Equation (4).

It should be noted that the different distortion orders strongly depend on the incidence point of the beam with respect to the surface wave, i.e., on the phase of the wave. If the beam passes through a maximum of the water wave, a convergent lens will mainly affect the beam, if it passes through a minimum, a divergent lens effect appears. If the beam propagates through the zero-crossing of the wave, mainly a beam deflection and a phase jitter will occur.

A previous experimental analysis revealed that low-order Taylor series orders, respectively Zernike polynomials (piston/stroke, tip/tilt and defocus) dominate the wavefront distortions [12]. Distortions of higher orders, i.e., with higher spatial frequency can be neglected at the considered flow measurement task. This can be easily understood since at the water surface the diameter of the laser beams is around some millimeters and therefore significantly smaller than the typical wavelength of the observed capillary waves of 50 mm. This wavelength results by considering the highest amplitude (mode) of the measured Fourier spectrum of 6 Hz and the estimated phase velocity of the surface wave of 0.3 m/s.

These preconditions define the spatial and temporal parameters of the AO system to be implemented. In general, several optical modulators are available for the correction of wavefront distortions, e.g., deformable membrane mirrors, micro-electro-mechanic-system (MEMS) mirror arrays and liquid-crystal spatial light modulators. In our former research work [11,12] we have employed a deformable membrane mirror exhibiting 17 electrostatic actuator elements and built-in piezoelectric tip-tilt unit. An obstacle of the deformable membrane mirror was its restricted defocus range due to the limited curvature of the membrane. Considering an optical imaging magnification from the mirror to the water surface of one, only defocuses up to about 0.3 diopters can be corrected. It is not enough at large heights of the surface waves of the

investigated experiment. In the next section we will present a new optical measurement system able to handle the correction of large distortions.

2.2 Smart Laser Interferometer with Electrically Tunable Lenses

In order to correct for large wavefront distortions exhibiting a strongly limited spatial bandwidth, only the first and second orders of the Taylor series are considered, see Equation (3). The approach is to employ a combination of electrically tunable lenses, used to correct the 2nd order distortion and two-axis galvanometric mirrors, used to correct the 1st order distortions. Electrically tunable lenses have been suggested and employed for several measurement tasks already [14–17]. In this paper a novel adaptive silicone membrane lens, provided by IMTEK, University of Freiburg, Laboratory for Microactuators, Germany, is inserted. The used principle is based on optofluidics [14]. A piezo-electric actuator is applied for the variation of the pressure of a fluid. It results in a change of the shape of a transparent silicon membrane. In consequence, the focal length of the lens can be steered by an electrical voltage of the piezo-electric actuator [14, 17]. The employed electrically tunable membrane lens offers several advantages:

- A high defocus range of up to ± 40 diopters can be covered.
- A 3 dB temporal bandwidth of over 60 Hz. It should be high enough to correct the distortions of the capillary waves at the current experiment.
- Due to its outer size of 20 mm diameter the tunable lens is ideal for being integrated into compact sensors.

To correct for 1st order aberrations, i.e., tip/tilt, two biaxial two-dimensional, electromagnetically driven steering mirror (Model OIM101, Optics in Motion LLC, USA) were used. It enables scanning over an angular range of $\pm 1.5^\circ$ (± 26 mrad) with < 2 μ rad resolution and a 3 dB bandwidth of > 550 Hz. Two Hartmann-Shack camera sensors (type Basler—piA640-210gm, supplied by Flexible Optical B.V., The Netherlands) were employed, one for each transmitted laser beam, to measure the wavefront distortions caused by the capillary waves on the free water surface. In Figure 1 the setup of the smart LDV interferometer is shown.

Based on the wavefront data of the Hartmann-Shack camera, the following actuating variables have to be computed to guarantee a complete control of the two partial beams:

- The focal lengths of the tunable lens for the first and second partial beam
- The deflections of the mirror in x-direction for the first and second partial beam
- The deflections of the mirror in y-direction for the first and second partial beam

Before the adjustment control can operate, a calibration has to be performed. Therefore electric signals are applied to the control system in the absence of the distortion, i.e. a resting air-water interface. The resulting changes of the wavefront are evaluated and the relationship between signals and wavefront deformation are stored as a transfer matrix. During the operation of the control loop the inverse procedure is used. The deviation of the measured wavefront from the default wavefront is calculated and multiplied with the inverse matrix to determine the electric signals which compensate the wavefront distortion. An integral controller is used as the control type, resulting in a vanishing control deviation. The control loop is realized as a twin system whose identical parts control both laser beams simultaneously. The number of performed control cycles per time unit depends on different parameters of the control loop. This control rate is mainly influenced by the number of evaluated spots of the Hartmann-Shack wavefront sensor. In the case of four evaluated spots a control rate of 1 kHz is achieved. In order to gain a sufficient sensitivity regarding the wavefront distortion, usually 20 spots are evaluated. Here the control loop operates at 540 Hz. Mainly due to the settling time of the PC-based controller, hence the latency time distortions with frequencies up to 42 Hz could be suppressed reliably. This is fast enough to cover the main components of the spectrum of the occurring capillary waves [12].

2.3 Performance of the Distortion Correction

To characterize the quality of the distortion correction of the AO system, different figures of merit can be considered. A primary quantity is the interference visibility, i.e., the modulation degree of the burst LDV signals. Moreover, the validation rate, i.e., the number of valid high SNR measurement signals with respect to the number of the total acquired

signals, can be used as a figure of merit as well. Although it depends on the interference visibility and also on the SNR, this quantity is more appropriate for the flow velocity measurements. The validation rate affects the measurement uncertainty and also the temporal resolution of the flow velocity.

Figure 1. Smart laser Doppler velocimeter (LDV) interferometer with two implemented electrically tunable lenses (TL) and two two-axis galvanometer mirrors (GM). The smart LDV compensates the wavefront distortions caused by the fluctuating air-water interface. A twin control loop was realized to control both partial laser beams simultaneously. In the overlapping area of the two laser beams a fringe system is generated. The scattered light from tracer particles moving through this fringe system is measured by the photodetector (PD). In result the flow velocity v is determined.

The experiments were performed in a water basin. A water pump was used to excite capillary surface waves in the basin which acted as the optical distortion. The distortion amplitude can be varied by changing the driving voltage of the pump. In order to investigate the LDV measurement properties, a moving pinhole was used as a scattering object. Below the basin an optical chopper rotated the pinhole at a constant speed v_0 . According to Equation (1) the measured Doppler signal frequency is given by $f = v_0/d$. In conclusion, variations of the signal frequency are mainly caused by changes of the fringe spacing d and therefore by the optical distortions from the fluctuating air-water interface. This procedure allows us to study the improvements by the used AO system, see Figures 2 and 3. In Figure 2 the mean validation rate is displayed in dependence of the mean amplitude of the distortion. The AO system results in a significant improvement for the validation rate. At distortion amplitudes, i.e., mean surface wave heights of $75 \mu\text{m}$ the validation rate is enhanced from 12% to 92% with the AO-based distortion correction. Also, compared to the former AO technique [11,12] a significant improvement has been achieved. The hypothesis to correct large distortion strokes by electrically tunable lenses and galvanometer mirrors has been confirmed. As a benefit, the measurement time can be reduced or more valid signals can be gathered in a predefined measurement time. The higher data rate also increases the temporal resolution, thus making it possible to evaluate spectrally broad turbulence, which is crucial for the investigation of complex flows [18–20]. Figure 3 shows the mean velocity measurement uncertainty in dependence of the mean distortion amplitude. The reason for the increased velocity standard deviation is that the spacing of the fringe system changes with the crossing angle but also with the position of the beam waist of the Gaussian beams. These effects are compensated with the tilting mirrors and the adaptive lenses, respectively. It can be seen that the velocity standard deviation is reduced significantly below mean surface wave amplitudes of about $100 \mu\text{m}$ when applying the AO correction.

Figure 2. Mean validation rate with and without distortion correction in dependence of the mean amplitude of the distortion, i.e., height of the surface water wave.

Figure 3. Relative standard deviation of the velocity measurement with and without distortion correction as a function of the mean amplitude of the distortion.

2.4 Smart Photonic and Optoelectronic Integrated Circuit

Based on the successful demonstration of the smart laser Doppler velocimeter (LDV) interferometer, see Figure 1, we have designed an integrated circuit measurement system, see Fig. 4. Electrically tunable optofluidics membrane lenses are used together with MEMS galvo mirrors. They allow a high miniaturization degree of the measurement chip in order to face the requirements of endoscopy and other keyhole access applications.

Figure 4.2.4 Smart photonic and optoelectronic integrated circuit using the Fresnel reflex as a laser guide star. Electrically-tunable lenses (TL), micro galvo mirrors (GM), diffractive optical elements (DOE) are employed in order to realize a miniaturized optical chip interferometer. The processing of the Fresnel reflex signals is not displayed.

3. CONCLUSIONS

Refractive index variations, caused by fluctuating refractive index fields or interfaces, can deteriorate the properties of velocity measurements. A lower rate of valid high SNR signals and an increased velocity uncertainty can be the consequences. To overcome these limitations, the principle of wavefront correction by means of AO was applied. AO is an emerging technology with constantly improving opportunities. Standardized fabrication processes, improved techniques and new methods significantly lower barriers of their employment. In this contribution, a smart Mach-Zehnder interferometer for flow velocity measurements was presented, that was equipped with a twin AO system to corrected wavefront distortions caused by a fluctuating air-water interface. Using the wavefront correction, the interference contrast and the number of valid high SNR signals was improved significantly. Measurements in the presence of optical distortions can be performed in a shorter time and with a higher statistical reliability. AO offers new perspectives for metrology at applications that have hardly been accessible by laser measurement techniques so far. The presented velocity measurements through disturbing fluid interfaces are important at several fields of fluid mechanics. At convection research, an improved understanding of heat transfer by turbulence can be achieved, which can enhance the energy efficiency of film cooling devices. Furthermore, in biomedical research, optical blood flow measurement can improve the investigation of diseases such as aneurysm and arteriosclerosis.

Acknowledgments

The authors acknowledge financial support from the German Research Foundation (DFG, grant Cz 55/30) by a Reinhart Koselleck project.

REFERENCES

- [1] Birch, K.P.; Downs, M.J. An Updated Edlén Equation for the Refractive Index of Air. *Metrologia* 1993, 30, 155–162.
- [2] Beckers, J.M. Adaptive Optics for Astronomy: Principles, Performance, and Applications. *Ann. Rev. Astron. Astrophys.* 1993, 31, 13–62.
- [3] Hardy, J.W. Adaptive Optics for Astronomical Telescopes; Oxford University Press: New York, NY, USA, 1998.
- [4] Glindemann, A.; Hippler, S.; Berkefeld, T.; Hackenberg, W. Adaptive Optics on Large Telescopes. *Exp. Astron.* 2000, 10, 5–47.
- [5] Tyson, R. Principles of Adaptive Optics, Third Edition; CRC Press: Boca Raton, FL, USA, 2010.
- [6] Roorda, A.; Romero-Borja, F.W.D.; III; Queener, H.; Hebert, T.; Campbell, M. Adaptive optics scanning laser ophthalmoscopy. *Opt. Express* 2002, 10, 405–412.
- [7] Hermann, B.; Fernández, E.J.; Unterhuber, A.; Sattmann, H.; Fercher, A.F.; Drexler, W.; Prieto, P.M.; Artal, P. Adaptive-optics ultrahigh-resolution optical coherence tomography. *Opt. Lett.* 2004, 29, 2142–2144.
- [8] Fuh, Y.K.; Hsu, K.C.; Fan, J.R. Rapid in-process measurement of surface roughness using adaptive optics. *Opt. Lett.* 2012, 37, 848–850.
- [9] Fuh, Y.K.; Fan, J.R. Experimental investigation of a flowing fluid layer on metal surface roughness measurement and aberration correction using adaptive optics. *Opt. Rev.* 2013, 20, 433–437.
- [10] Klepikov, K.E.; Kulybin, V.M.; Rinkevichius, B.S. Using the principles of adaptive optics in laser Doppler anemometry. *Vsesoiuznyi Seminar po Opticheskim Metodam Issledovaniia Potokov*, 1st, Novosibirsk, USSR, 23–25 May 1989, In Russian.
- [11] Büttner, L.; Leithold, C.; Czarske, J. Advancement of an Interferometric Flow Velocity Measurement Technique by Adaptive Optics. *Int. J. Optomech.* 2014, 8, 1–13.
- [12] Büttner, L.; Leithold, C.; Czarske, J. Interferometric Velocity Measurements through a fluctuating Gas-Liquid Interface Employing Adaptive Optics. *Opt. Express* 2013, 21, 30653–30663.
- [13] Czarske, J.; Büttner, L.; Razik, T.; Müller, H. Boundary layer velocity measurements by a laser Doppler profile sensor with micrometre spatial resolution. *Measurement Sci. Technol.* 2002, 13, 1979–1289.
- [14] Schneider, F.; Draheim, J.; Kamberger, R.; Waibel, P.; Wallrabe, U. Optical characterization of adaptive fluidic silicone-membrane lenses. *Opt. Express* 2009, 17, 11813–11821.
- [15] Khan, S.A.; Riza, N.A. Demonstration of a No-Moving-Parts Axial Scanning Confocal Microscope Using Liquid Crystal Optics. *Opt. Commun.* 2006, 265, 461–467.
- [16] Riza, N.A.; Sheikh, M.; Webb-Wood, G.; Kik, P.G. Demonstration of three-dimensional optical imaging using a confocal microscope based on a liquid-crystal electronic lens. *Opt. Eng. J.* 2008, 47, 063201:1–063201:9.
- [17] Koukourakis, N.; Finkeldey, M.; Stürmer, M.; Leithold, C.; Gerhardt, N.C.; Hofmann, M.R.; Wallrabe, U.; Czarske, J.W.; Fischer, A. Axial scanning in confocal microscopy employing adaptive lenses (CAL). *Opt. Express* 2014, 22, 6025–6039.
- [18] Fischer, A.; Schlüßler, R.; Haufe, D.; Czarske, J. Lock-in spectroscopy employing a high-speed camera and a micro-scanner for volumetric investigations of unsteady flows. *Opt. Lett.* 2014, 39, 5082–5085.
- [19] Fischer, A.; König, J.; Czarske, J.; Peterleithner, J.; Woisetschlager, J.; Leitgeb, T. Analysis of flow and density oscillations in a swirl-stabilized flame employing highly resolving optical measurement techniques. *Exp. Fluids* 2013, doi:10.1007/s00348-013-1622-3.
- [20] Neumann, M.; Friedrich, C.; Kriegseis, J.; Grundmann, S.; Czarske, J. Determination of the phase-resolved body force produced by a dielectric barrier discharge plasma actuator. *J. Phys. D*, 46, 042001 (2013)